

# BTC 7941



- 1. WWW:**  
Launch to your Internet browser.
- 2. Shortcut:**  
Access to the documents and programs most often used.
- 3. My Favorite:**  
Launch to your Internet browser and open My Favorite menu.
- 4. WWW Search:**  
Launch to your Internet browser and open Search Window.
- 5. Volume down:**  
Lower the volume of your audio output to the speakers.
- 6. Volume up:**  
Raise the volume of your audio output to the speakers.
- 7. Mute:**  
Toggle this button to mute or resume the sound output.
- 8. Previous/F.B.:**  
Skip backward to the previous file/keep pressing to skip backward and start to play.
- 9. Play/Pause:**  
Start to play audio/video file in the current track. Repress this button to pause.
- 10. Stop:**  
Stop the playing.
- 11. Next/F.F.:**  
Skip forward to the next file/keep pressing to skip forward and start to play.
- 12. Eject:**  
Eject the CD title.
- 13. Power off:**  
Press to power down the system.
- 14. Sleep:**  
Press to put the system to sleep.
- 15. Wake up:**  
Press to wake up the system.

## Electrical Characteristics

|                             |                                       |
|-----------------------------|---------------------------------------|
| Mode Selection              | : PC/AT & PS/2                        |
| Input power                 | : 5Vdc, 100mA                         |
| Switch activation mechanism | : Membrane                            |
| Serial data output          | : Serial format, TTL level compatible |

## Physical & Mechanical Characteristics

|                                    |  |
|------------------------------------|--|
| Model no. (key numbers)            | : BTC 7941(119/120/122/124)                                      |
| Languages                          | : U.S. / European / Brazilian / Japanese                         |
| Connector & pin assignment         | : DIN 5-pin, 45° pitch or<br>Mini-DIN 6-Pin, 36° pitch available |
| Travel distance                    | : 3.5 ± 0.5 mm   |
| Peak load before make (normal key) | : 55 ± 20 g  |
| Keyboard dimension                 | : 466(L)x247(W)x38(H)mm  |
| Keyboard weight                    | : 1.3 kg   |
| Packing information                |  |
| 1 pc/box                           | : 480(L)x305(W)x54(H)mm<br>: 1.55 kg                             |
| 10 pcs/carton                      | : 510(L)x327(W)x625(H)mm<br>: 17 kgs                             |
| Container load                     | : 2660 pcs/20'<br>: 5900 pcs/40'                                 |

## Environmental Operating Conditions

|                       |                              |
|-----------------------|------------------------------|
| Operating temperature | : 0 to 50°C                  |
| Storage temperature   | : -40 to 70°C                |
| Humidity              | : 20% to 90%, non-condensing |
| Altitude              | : -1000 ft to 10000 ft       |

## Electromagnetic Characteristics (EMC)

|        |  |
|--------|--|
| EMI    | : FCC part 15, subpart B, class B, C-tick, CNS, VCCI |
| SAFETY | : TÜV, UL and CSA                                    |
| CE     | : EN50081-1 & EN50082-1 (89/336/EEC)                 |

## Trademarks:

- IBM, PC/AT and PS/2 are registered trademarks of International Business Machines Corporation.
- Microsoft, Windows NT, Windows, and the Windows Logo are registered trademarks of Microsoft Corporation in the United States and/or other countries.

**BTC**<sup>®</sup> BEHAVIOR TECH COMPUTER CORP.

<http://www.btc.com.tw>

### Headquarters :

Taiwan office: TEL:(886)-2-2761-5911  
FAX:(886)-2-2767-8036

### U.S. Offices:

California: TEL:(1)-510-657-3956 FAX:(1)-510-657-3965  
BTC Latin: TEL:(1)-305-477-4596 FAX:(1)-305-477-9689

### European Offices:

The Netherlands: TEL:(31)-10-264-2444 FAX:(31)-10-264-2458  
France: TEL:(33)-2-41721650 FAX:(33)-2-41721659

### Korean Office:

TEL:(82)-32-579-0143 FAX:(82)-32-579-3605